














TK-802R General Quick Reference Sheet

Command	Hot Keys	Front Panel Button	OSD	Description
Show OSD Menu	Scroll Lock + Scroll Lock + Space Bar	—	—	Activates OSD menu
OSD Menu Timeout (5-99 seconds)	—	—	Use arrow keys to select OSD, then hit enter. Enter the desired time and then hit enter.	Specify the timeout for OSD menu [default = 10 seconds; range = 5-99 seconds]
Select Computer	Daisy Chain Scroll Lock + Scroll Lock + (A) + (B) + (Y) (Z) (AB) = bank number (YZ) = 2-digit channel number	Press push button for a specific port on the switch	Use arrow keys to select and then hit enter	Select the active bank (switch) and channel (computer)
Next Lower Channel	Scroll Lock + Scroll Lock + ↑	—	Use arrow keys to select and then hit enter	Select the next lower connected channel. Only works within active bank
Next Higher Channel	Scroll Lock + Scroll Lock + ↓	—	Use arrow keys to select and then hit enter	Select the next higher connected channel. Only works within active bank
Next Lower Bank	Scroll Lock + Scroll Lock + Page Up	—	Page Up	Select the next lower bank when multiple switches are daisy-chained
Next Higher Bank	Scroll Lock + Scroll Lock + Page Down	—	Page Down	Select the next higher bank when multiple switches are daisy-chained
Reset/Initialize KVM	Scroll Lock + Scroll Lock + END	—	—	Resets/reboot/initialize daisy-chain and activates password protection).
Load Factory Default	Scroll Lock + Scroll Lock + R	—	—	Restore the EEPROM settings to the factory default (except for password)
Find Computer by Name	Scroll Lock + Scroll Lock + F	—	—	Search presence of a specific computer by name
Change Computer Name	—	—	Use arrow keys to select, then hit Insert to edit	Change the computer name

TK-802R General Quick Reference Sheet

Command	Hot Keys	Front Panel Button	OSD	Description
Autoscan	 +  + 	—	—	Autoscan through every connected channel for quick browsing of each channel
Autoscan with Programmable Delay Time	—	—	Use arrow keys to select SCAN , then hit enter. Enter the desired time and then hit enter	Specify autoscan delay time [default = 10 seconds; range = 5~99 seconds]
Stop Autoscan		Press any button	—	End Autoscan activity
Autoscan Beep Sound On/Off	 +  + 	—	—	Toggle On/Off beep during autoscan mode
Enable/Disable Password Configuration	—	—	Use arrows to select PWD CONFIG and then hit enter. Hit enter again when Enable? or Disable? appears. Use the reset/initialize KVM hot key to ensure the setting is saved	Enable/disable password protection [default = disable]
Change Password	—	—	Use arrows to select PWD CHANGE and then hit enter. Enter the current password, hit enter and enter the new password	Change the password [default password = 00000000; password length <= 8 characters]

Note:

- The hot key sequence  +  +  denotes that you should hit the individual key consecutively one at a time, not simultaneously.
- After pressing the Scroll Lock key, you have 2 seconds to press the Scroll Lock key again. You then have another 2 seconds to press a command key. A beep confirms that the KVM switch is in "hot key" mode. If you do not press a key within 2 seconds, the switch will exit hot key mode.
- OSD Menu control is only available when the OSD menu is activated. To activate the OSD menu, use the hot key sequence  +  + . When the OSD Menu is active, the mouse will be locked until you exit the OSD Menu.