




Guide d'installation rapide 

TU3-SA
1.01

Table of Contents

Français	1
1. Avant de commencer	1
2. Installation du matériel	2
3. Disque dur Accès sur TU3-SA	4
Troubleshooting	5



Contenu de l'emballage

- TU3-SA
- Guide d'installation rapide en plusieurs langues
- Adaptateur secteur (12V DC, 2A)

Configuration du système

- USB Port: 3.0, 2.0 ou 1.1
- 2.5" ou 3.5" SATA I/II Hard Drive

SE supportés	Microprocesseur	Mémoire
Windows 7 (32/64-bit)	1GHz ou supérieur	1GB RAM ou supérieur
Windows Vista (32/64-bit)	800MHz ou supérieur	512MB RAM ou supérieur
Windows XP (32/64-bit)	300MHz ou supérieur	256MB RAM ou supérieur

Remarque:

1. Le disque dur n'est PAS fourni.
2. Certains systèmes d'exploitation ne supportent pas l'USB 3.0.

2. Installation du matériel


1. Connectez votre disque dur SATA à la TU3-SA.



Remarque:

Lorsque vous connectez un 2,5 "SATA disque dur, alimentation externe n'est pas nécessaire. Passer à l'étape 4.

2. Raccordez le cordon d'alimentation à l'adaptateur secteur AC et ensuite à une prise de courant.



3. Branchez l'adaptateur secteur au TU3-SA.

4. Branchez le câble USB Type A Connecteur mâle sur le TU3-SA dans un port USB disponible sur votre ordinateur.



ENGLISH

FRANÇAIS

DEUTSCH

ESPAÑOL

РУССКИЙ

5. Les pilotes s'installeront automatiquement.

Remarque:

Nous vous recommandons de formater tout d'abord un tout nouveau disque dur. Veuillez consulter la question 2 de la partie dépannage pour plus d'informations.

L'installation est maintenant complète

Si vous désirez des informations détaillées sur la configuration et les paramètres avancés du **TU3-SA**, veuillez consulter la rubrique Dépannage, le guide de l'utilisateur sur CD-ROM ou le site Internet de TRENDnet sur <http://www.trendnet.com>.

Enregistrez votre produit

Afin d'être sûr de recevoir le meilleur niveau de service clientèle et le meilleur support possibles, veuillez prendre le temps d'enregistrer votre produit en ligne sur: www.trendnet.com/register Nous vous remercions d'avoir choisi Trendnet

1. My computer does not recognize the TU3-SA. What should I do?

1. Verify that the computer meets the minimum requirements as listed in section 1.
2. Make sure that you have plugged in the power adapter into the unit and the power cord into an available power outlet.
3. Access the device manager and verify the TU3-SA is installed properly.
 1. To access the device manager on Windows 7, click on the Windows icon on the bottom left-hand corner, click **Computer**, click **System Properties** and then click **Device Manager**. Double click on **Universal Serial Bus Controllers**. Make sure that **USB Mass Storage Device** is listed and there is no yellow question mark or exclamation point.
 2. To access the device manager on Windows Vista, right-click **Computer**, click **Properties** and then click **Device Manager**. Double click on **Universal Serial Bus Controllers**. Make sure that **USB Mass Storage Device** is listed and there is no yellow question mark or exclamation point.
 3. To access the device manager on Windows XP, right-click **My Computer**, click **Properties**, click the Hardware tab, and then click **Device Manager**. Right click on My Computer → **Properties**. Double click on **Universal Serial Bus Controllers**. Make sure that **USB Mass Storage Device** is listed and there is no yellow question mark or exclamation point
4. Try plugging the device into a different USB port on your computer.

2. How do I format my brand new hard drive with the TU3-SA?

1. For Windows 7/Vista, right click on **Computer** or **My Computer** and select **Manage**. When the **Computer Management** screen appears, click on **Disk Management**. Right click on the hard drive and click **New Simple Volume**. Follow the **New Simple Volume wizard** and then click **Finish**.
2. For Windows XP, go to **Start** → **Settings** → **Control Panel** → **Administrative Tools** → **Computer Management** → **Disk Management**. If the Initialize and Convert Disk Wizard appears, click **Cancel**. Right click the **Unknown** drive, click Initialize and then click **OK**. Right click on the unallocated region of the hard drive and select **New Partition**. Follow the **New Partition Wizard** instructions then click **Finish**. The hard drive will automatically start the formatting process.

Note: Make sure that the selected hard drive is not your C or D drive. Also make sure that the selected hard drive is connected to the TU3-SA.

3. My computer does not list any drives? What should I do?

1. Access the device manager and verify the hard drive is installed properly.
 1. To access the device manager on Windows 7, click on the Windows icon on the bottom left-hand corner, click **Computer**, click **System Properties** and then click **Device Manager**. Double click on **Disk Drives**. Make sure that **USB Device** is listed and there is no yellow question mark or exclamation point.
 2. To access the device manager on Windows Vista, right-click **Computer**, click **Properties** and then click **Device Manager**. Double click on **Disk Drives**. Make sure that **USB Device** is listed and there is no yellow question mark or exclamation point.
 3. To access the device manager on Windows XP, right-click **My Computer**, click **Properties**, click the Hardware tab, and then click **Device Manager**. Right click on **My Computer** → **Properties**. Double click on **Disk Drives**. Make sure that USB Device is listed and there is no yellow question mark or exclamation point.
2. If you are attaching a brand new hard drive, format the drive. Please refer to question 2 for more information.

If you still encounter problems or have any questions regarding the **TU3-SA**, please contact TRENDnet's Technical Support Department.

Déclaration de conformité



Coordonnées du fournisseur:

Nom:

TRENDnet, Inc.

Adresse:

20675 Manhattan Place

Torrance, CA 90501

USA

Détails du produit:

Nom du produit:

USB 3.0 to SATA Adapter

Modèle:

TU3-SA

Nom Commercial:

TRENDnet



Détails standard applicable:

EN 55022 : 2006 + A1 : 2007

EN 61000-3-2 : 2006

EN 61000-3-3 : 1995 + A1 : 2001 + A2 : 2005

EN 55024 : 1998 + A1 : 2001 + A2 : 2003

Déclaration:

Le produit est conforme aux exigences de la directive 2004/108/EC du Conseil (Parlement européen) sur la directive EMC.

Je déclare par la présente que les produits et appareils mentionnés ci-dessus sont conformes aux standards et aux dispositions des directives.

Sonny Su

Full Name

February 17, 2011

Date

Director of Technology

Position / Title

Signature

Certifications

This equipment has been tested and found to comply with FCC and CE Rules.

Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference.
- (2) This device must accept any interference received. Including interference that may cause undesired operation.



Waste electrical and electronic products must not be disposed of with household waste. Please recycle where facilities exist. Check with you Local Authority or Retailer for recycling advice.



NOTE: THE MANUFACTURER IS NOT RESPONSIBLE FOR ANY RADIO OR TV INTERFERENCE CAUSED BY UNAUTHORIZED MODIFICATIONS TO THIS EQUIPMENT. SUCH MODIFICATIONS COULD VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT.

ADVERTENCIA

En todos nuestros equipos se mencionan claramente las características del adaptador de alimentación necesario para su funcionamiento. El uso de un adaptador distinto al mencionado puede producir daños físicos y/o daños al equipo conectado. El adaptador de alimentación debe operar con voltaje y frecuencia de la energía eléctrica domiciliar existente en el país o zona de instalación.



Product Warranty Registration

Please take a moment to register your product online.
Go to TRENDnet's website at <http://www.trendnet.com/register>