How do I add a Camera to the TRENDnetVIEW Pro Software?

After the camera has been configured and set up on your network, you can use SecurView Pro to record video via motion detection. Insert the CD-ROM to the computer and click **Install TRENDnetVIEW Pro Software** in the Autorun.

Double click the **TRENDnetVIEW Pro** short cut on desktop.

1. Click on the desktop icon on the tool bar and select **Add, configure or delete camera device** option

2. Click **Next** and select your Network Adapter then **Next.**

3. Enter your camera's model name or any name you might want to use and click on **Properties** button

4. Select TRENDnet model (TV-IP762IC) and click **OK**.

5. The **Properties** window will re-appear, click on **Access** tab and enter your camera's IP, port and password information (Please set the static IP and assigned port on the camera prior to adjust setting on the TRENDnetVIEW Pro. In this example, the camera has a static IP address 192.168.10.50 and 80 as port number.) then click **OK**.

Here is an example to set the static IP and assigned port on your camera, or refer more details with your router user's guide:

6. Click **Next** on the Camera Setup Wizard.

7. Follow the wizard instructions and then click **Finish**. (For schedule/motion detection recording settings, please refer to **TRENDnetVIEW Pro** User's Guide for configuration details).

8. Camera is added and shown in the viewing panel.

For other advanced features in **TRENDnetVIEW Pro** software, please refer to the **TRENDnetVIEW Pro** User's Guide on the CD.