

TEG-S2400i TFTP Firmware Upgrade Procedure

SS05052004

1. Release Note:

Ver. 10.04.01

1. Update from Ver. 10.03.02.
2. When saving/restoring the Switch's configuration, the Switch's MAC address will not be saved/restored. This way, user can save a certain configuration file and clone it to multiple Switches.

(Note: firmware version 03.03.06 or earlier is not able to upgrade to version 10.04.01 or newer firmware.)

2. Firmware upgrade requirements:


Software: TFTP Server Software (such as TFTP.D.EXE)

Hardware: A PC with network adapter connects to TEG-S2400i and the PC is able to access the TEG-S2400i's configuration page with web browser.

3. Please **note** that after the firmware upgrade, all the settings in the Switch are changed back to default settings (including the IP address). Please keep a record of the Switch's configurations and then manually put them back after completing the upgrade.

4. Below is the firmware upgrade instruction using TFTP.D.EXE software.

- RUN TFTP program




- Copy firmware file to C: drive. (e.g. **C:\v100401.BIN**)
- From TFTP software, click on "File", select "Set Root", enter **C:** as the "root directory", and click "Ok".



5. Go to Web configuration page for TEG-S2400i, click on “**TFTP Update Firmware**” under “**Menu**” on the left, type TFTP Server IP address (the IP address of the computer that is running the TFTP Server software), type in the firmware file name (e.g. **v100401.bin**) and then click “**Apply**”.



6. After the Download completed, click “**Upgrade Firmware**” to start the upgrade. (**Note:** do not interrupt the firmware upload.)



7. After uploading the firmware, click “Reboot” to restart the system.
8. This completes the firmware upgrade.