


TK-803R / TK-1603R KVM General Quick Reference Sheet

Command	Hot Keys	Front Panel Button	Description
Select Computer	TK-803R  +  +  (Y) = 1-digit port number (1-8) TK-1603R  +  +  +  (YZ) = 2-digit port number (01-16)	Press the push button for a specific port to switch to that computer	Select the desired computer
Next Higher Computer Channel	 +  + 	Press push button for a specific port on the switch	Select the next higher available computer
Next Lower Computer Channel	 +  + 	Press push button for a specific port on the switch	Select the next lower available computer
Autoscan	 +  + 	—	Autoscan through every connected channel for quick screen browsing of each channel
Autoscan with Programmable Delay Time	 +  +  +  (X) fx = 0 ~ 9 1 = 10 seconds 2 = 20 seconds 3 = 30 seconds 4 = 40 seconds 5 = 50 seconds 6 = 60 seconds 7 = 70 seconds 8 = 80 seconds 9 = 90 seconds 0 = 100 seconds	—	Autoscan through every connected channel for quick screen browsing of each channel in (10-100 seconds)
Stop Autoscan		Press any button	Terminate autoscan activity
Autoscan Beep Sound On/Off	 +  + 	—	Terminate autoscan activity.
Mouse/Keyboard Reset Console	 +  + 	—	Toggle On/Off beep sound during autoscan mode
Restore to Factory Defaults	 +  + 	—	Resets Mouse/Keyboard
Define Hot key Sequence (Default = Scroll Lock + Scroll Lock + Scroll Lock)	 +  +  +  (Y) = Scroll Lock, Caps Lock, Esc, F12 or Num Lock	Press and hold down button 4 for over 8 seconds, then release the button and press  (Y) = Scroll Lock, Caps Lock, Esc, F12 or Num Lock	Select the hot key preceding sequence among 5 options

Note:

- The hot key sequence  +  +  denotes that you should hit the individual key consecutively one at a time, not simultaneously.
- After pressing the Scroll Lock key, you have 2 seconds to press the Scroll Lock key again. You then have another 2 seconds to press a command key. A beep confirms that the KVM switch is in "hot key" mode. If you do not press a key within 2 seconds, the switch will exit hot key mode.