



Lühike paigaldusjuhend



TK-EX3
1.01

Eesti	
1. Enne alustamist	1
2. Kuidas paigaldada	2
Technical Specifications	6
Tõrkeotsing	7



Pakendi sisu

- 1 x Saatja (kohalik seade)
- 1 x Vastuvõtja (kaugseade)
- Mitmekeelne lühike paigaldusjuhend
- Toiteplokk (9V DC, 1A)
- VGA kombinatsiooniga kaabel (1.2m / 4ft.)
- USB A-tüüpi et B-tüüpi kaabel

Minimaalsed nõuded süsteemile

- PS/2 klaviatuur
- PS/2 hiir
- VGA ühilduv monitor
- Cat.5/5e/6 Ethernet Cable
- USB A-tüüpi et B-tüüpi kaabel (valikuline)
- Windows 7(32/64-bit)/Vista(32/64-bit)/XP(32/64-bit)/2000/2003 Server/Me/98SE

2. Kuidas paigaldada

1. Lülitage oma arvuti ja monitorid välja OFF.



2. Ühendage PS/2 klaviatuur ja PS/2 hiir TK-EX3 vastuvõtja (kaugseadme) külge.



3. Ühendage monitor TK-EX3 vastuvõtja (kaugseadme) külge.



Ühendage arvuti USB-sse

4. Kasutage kombineeritud VGA kaablit, et ühendada teie arvuti KVM pikendajaga.



TK-EX3 vastuvõtjasse
(kohalik seade)



Arvutisse

5. Ühendage kaasasolev USB kaabli A otsik oma arvutiga.



TK-EX3 saatjasse
(kohalik seade)

6. Ühendage kaasasolev USB kaabli B otsik TK-EX3 saatja (kohaliku seadme) USB porti.



7. Liikuge sammu 9.

Ühendage arvuti PS/2 porti.

8. Use the VGA combination cable to connect your computer to the TK-EX3 Transmitter (local device).

TK-EX3 saatjasse (kohalik seade)



Arvutisse

Hiire porti

Klaviatuuri porti

VGA porti



9. Ühendage Cat.5/5e/6 Etherneti kaabel saatja (kohaliku seadme) Etherneti pordist vastuvõtja (kaugseadme) Etherneti porti.



10. Ühendage kaasasolev toiteplokk vastuvõtjaga (kaugseadmega) ja siis ühendage vooluvõrku.



11. Lülitage sisse arvuti ja kõik ühendatud monitorid.



Teie paigaldamine on nüüd lõppenud

Teie seadmete registreerimine

Et kindlustada teid parima teeninduse ja toega, palun leidke moment, et registreerida teie toode OnLines www.trendnet.com/register Täname, et te valisite TRENDnet'i.

Technical Specifications

Connections	Connect to a computer or KVM switch
Connectors	Transmitter (local device): HDB 15-pin VGA USB type B RJ-45 port Receiver (remote device): HDB 15-pin VGA Mini din female RJ-45 port Power connector
Cables (included)	1 x VGA cable (VGA to VGA and PS/2), 1.2 m / 4 ft. 1 x USB cable (type A to type B), 1.2 m / 4 ft.
Supported OS	Windows 7/Vista/XP/2000, Linux
Resolution	Up to 100 m (328 ft.) with 1600 x 1200 resolution Up to 150 m (490 ft.) with 1280 x 1024 resolution
Power	9V DC, 1A
LEDs	Power, Link
Dimensions (L x W x H)	130 x 65 x 25 mm (5 x 2.6 x 1 in.)
Weight	Transmitter (local device): 275 g (9.7 oz.) Receiver (remote device): 290 g (10 oz.)
Temperature	Operating: 0° ~ 40° C (32° ~ 104° F) Storage: -20° ~ 60° C (-4° ~ 140° F)
Humidity	Max. 90% (Non-Condensing)
Certifications	CE, FCC

1. Kus ma peaksin kasutama kaasas olevat välimist toiteplokki?

Te peate kaasas olevat välimist toiteplokki kasutama TK-EX3 KVM switchiga.

2. Mul on TK-EX3 ühendatud korralikult, kuid minu klaviatuur ja hiir ei tööta. Mida ma peaksin tegema?

1. Veenduge, et teie toiteplokk on ühendatud TK-EX3 switchiga.
2. Kontrollige, et teie klaviatuur ja hiir töötavad korralikult, kui need ühendada otse teie arvuti PS/2 portidesse.
3. Proovige kasutada mõnda teist PS/2 klaviatuuri ja hiirt.

3. Minu videopilt on moonutuses, kui ma ühendan monitori TK-EX3 vastuvõtjaga (kaugseadmega). Mida ma peaksin tegema?

1. Te saate reguleerida pildi kvaliteeti kasutades Gain (resolutsiooni reguleerimiseks) ja Equalization (kontrasti reguleerimiseks) nuppe TK-EX3 vastuvõtjal (kaugseadmel).
2. Kui te kasutate kaablit, mis on pikem kui 100 meetrit, siis peate vähendama oma monitori resolutsiooni kuni 1280 x 1024. Järgige millised on TK-EX3 maksimum kaablite pikkused:

Kuni 100m - 1600 x 1200 resolutsioon

Kuni 150m - 1280 x 1024 resolutsioon

Kui teil on jätkuvalt probleeme või küsimusi **TK-EX3** kohta, palun võtke ühendust TRENDneti tehnilise toega.

Limited Warranty

TRENDnet warrants its products against defects in material and workmanship, under normal use and service, for the following lengths of time from the date of purchase.

TK-EX3 - 2 Year Limited Warranty AC/DC Power Adapter, Cooling Fan and Power Supply carry a 1 year limited warranty

If a product does not operate as warranted during the applicable warranty period, TRENDnet shall reserve the right, at its expense, to repair or replace the defective product or part and deliver an equivalent product or part to the customer. The repair/replacement unit's warranty continues from the original date of purchase. All products that are replaced become the property of TRENDnet. Replacement products may be new or reconditioned. TRENDnet does not issue refunds or credit. Please contact the point-of-purchase for their return policies.

TRENDnet shall not be responsible for any software, firmware, information, or memory data of customer contained in, stored on, or integrated with any products returned to TRENDnet pursuant to any warranty.

There are no user serviceable parts inside the product. Do not remove or attempt to service the product by any unauthorized service center. This warranty is voided if (i) the product has been modified or repaired by any unauthorized service center, (ii) the product was subject to accident, abuse, or improper use (iii) the product was subject to conditions more severe than those specified in the manual.

Warranty service may be obtained by contacting TRENDnet within the applicable warranty period and providing a copy of the dated proof of the purchase. Upon proper submission of required documentation a Return Material Authorization (RMA) number will be issued. An RMA number is required in order to initiate warranty service support for all TRENDnet products. Products that are sent to TRENDnet for RMA service must have the RMA number marked on the outside of return packages and sent to TRENDnet prepaid, insured and packaged appropriately for safe shipment. Customers shipping from outside of the USA and Canada are responsible for return shipping fees. Customers shipping from outside of the USA are responsible for custom charges, including but not limited to, duty, tax, and other fees.

WARRANTIES EXCLUSIVE: IF THE TRENDNET PRODUCT DOES NOT OPERATE AS WARRANTED ABOVE, THE CUSTOMER'S SOLE REMEDY SHALL BE, AT TRENDNET'S OPTION, REPAIR OR REPLACE. THE FOREGOING WARRANTIES AND REMEDIES ARE EXCLUSIVE AND ARE IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED OR IMPLIED, EITHER IN FACT OR BY OPERATION OF LAW, STATUTORY OR OTHERWISE, INCLUDING WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. TRENDNET NEITHER ASSUMES NOR AUTHORIZES ANY OTHER PERSON TO ASSUME FOR IT ANY OTHER LIABILITY IN CONNECTION WITH THE SALE, INSTALLATION MAINTENANCE OR USE OF TRENDNET'S PRODUCTS.

TRENDNET SHALL NOT BE LIABLE UNDER THIS WARRANTY IF ITS TESTING AND EXAMINATION DISCLOSE THAT THE ALLEGED DEFECT IN THE PRODUCT DOES NOT EXIST OR WAS CAUSED BY CUSTOMER'S OR ANY THIRD PERSON'S MISUSE, NEGLIGENCE, IMPROPER INSTALLATION OR TESTING, UNAUTHORIZED ATTEMPTS TO REPAIR OR MODIFY, OR ANY OTHER CAUSE BEYOND THE RANGE OF THE INTENDED USE, OR BY ACCIDENT, FIRE, LIGHTNING, OR OTHER HAZARD.

LIMITATION OF LIABILITY: TO THE FULL EXTENT ALLOWED BY LAW TRENDNET ALSO EXCLUDES FOR ITSELF AND ITS SUPPLIERS ANY LIABILITY, WHETHER BASED IN CONTRACT OR TORT (INCLUDING NEGLIGENCE), FOR INCIDENTAL, CONSEQUENTIAL, INDIRECT, SPECIAL, OR PUNITIVE DAMAGES OF ANY KIND, OR FOR LOSS OF REVENUE OR PROFITS, LOSS OF BUSINESS, LOSS OF INFORMATION OR DATE, OR OTHER FINANCIAL LOSS ARISING OUT OF OR IN CONNECTION WITH THE SALE, INSTALLATION, MAINTENANCE, USE, PERFORMANCE, FAILURE, OR INTERRUPTION OF THE POSSIBILITY OF SUCH DAMAGES, AND LIMITS ITS LIABILITY TO REPAIR, REPLACEMENT, OR REFUND OF THE PURCHASE PRICE PAID, AT TRENDNET'S OPTION. THIS DISCLAIMER OF LIABILITY FOR DAMAGES WILL NOT BE AFFECTED IF ANY REMEDY PROVIDED HEREIN SHALL FAIL OF ITS ESSENTIAL PURPOSE.

Governing Law: This Limited Warranty shall be governed by the laws of the state of California.

Some TRENDnet products include software code written by third party developers. These codes are subject to the GNU General Public License ("GPL") or GNU Lesser General Public License ("LGPL").

Go to <http://www.trendnet.com/gpl> or <http://www.trendnet.com> Download section and look for the desired TRENDnet product to access to the GPL Code or LGPL Code. These codes are distributed WITHOUT WARRANTY and are subject to the copyrights of the developers. TRENDnet does not provide technical support for these codes. Please go to <http://www.gnu.org/licenses/gpl.txt> or <http://www.gnu.org/licenses/lgpl.txt> for specific terms of each license.

PWP05202009v2

Sertifikaadid:

Seade on testitud ning vastab FCC ja CE reeglitele.

Seade vastab järgmistele tingimustele:

(1) Seade ei tohi põhjustada ohtlikke häireid.

(2) Seade peab võtma vastu kõiki signaale, sealhulgas signaale, mis võivad põhjustada soovimatuid häireid seadme töös.



Elektri- ja elektroonikatoodete jäätmeid ei tohi ära visata koos olmejäätmetega. Abivahendite olemasolu korral palume ümbertöötlemiseks sorteerida. Jäätmete ümbertöötlemise kohta küsige nõu oma kohalikul jaemüüjalt.



MÄRKUS: TOOTJA EI VASTUTA ÜHEGI TV VÕI RAADIO HÄIRE EEST, MIS ON PÕHJUSTATUD SEADME LUBAMATUST ÜMBEREHITAMISEST. IGASUGUNE ÜMBERMODIFITSEERIMINE TÜHISTAB AUTORIVASTUTUSE SEADMELE.



Product Warranty Registration

Please take a moment to register your product online.
Go to TRENDnet's website at <http://www.trendnet.com/register>