



Guia de Instalação Rápida



TK-EX3
1.01

Português	
1. Antes de Iniciar	1
2. Como Instalar	2
.....	
Technical Specifications	6
Troubleshooting	7



Conteúdo da Embalagem

- 1 x Transmissor (dispositivo local)
- 1 x Receptor (dispositivo remoto)
- Guia Multilínguas de Instalação Rápida
- Adaptador de Tensão Externo (9V DC, 1A)
- Cabo combinado VGA (1.2m / 4ft.)
- USB tipo A para o cabo do tipo B

Requisitos Mínimos do Sistema

- Teclado PS 2
- Mouse PS 2
- Monitor VGA Compatível
- Cabo Cat.5/5e/6 Ethernet
- USB tipo A para o cabo do tipo B (Opcional)
- Windows 7(32/64-bit)/Vista(32/64-bit)/XP(32/64-bit)/2000/2003 Server/Me/98SE

2. Como instalar

1. Desligue adequadamente seu computador e monitores.



2. Conecte o teclado PS/2 e o mouse PS/2 ao receptor do TK-EX3 (dispositivo remoto).



3. Conecte o monitor ao receptor do TK-EX3 (dispositivo remoto).



Conectando a um Computador USB

4. Use o cabo combinado VGA para conectar seu PC ao Extensor KVM.



Ao Transmissor TK-EX3
(dispositivo local)



Ao Computador

5. Conecte o terminal tipo A do cabo USB fornecido ao seu computador.



Ao Transmissor TK-EX3
(dispositivo local)

6. Conecte o terminal tipo B do cabo USB fornecido à porta USB do transmissor TK-EX3 (dispositivo local).



7. Siga para o passo 9.

Conectando a Computador PS/2

8. Use o cabo combinado VGA para conectar seu computador ao Transmissor TK-EX3 (dispositivo local).

Ao Transmissor TK-EX3 (dispositivo local)



Ao Computador

À porta de Mouse

À porta de Teclado

À porta VGA



9. Conecte um cabo Ethernet Cat.5/5e/6 da porta Ethernet do Transmissor (dispositivo local) à porta Ethernet do Receptor (dispositivo remoto).



10. Conecte o Adaptador de Tensão fornecido ao Receptor (dispositivo remoto) e então a uma tomada elétrica.



11. Ligue seu computador e todos os monitores conectados.



Sua instalação agora está completa.

Registre Seu Produto

Para garantir o alto nível do serviço e suporte ao consumidor, por favor tire um minuto para registrar seu produto Online em: www.trendnet.com/register Agradecemos por ter escolhido TRENDnet.

Technical Specifications

Connections	Connect to a computer or KVM switch
Connectors	Transmitter (local device): HDB 15-pin VGA USB type B RJ-45 port Receiver (remote device): HDB 15-pin VGA mini din female RJ-45 port Power connector
Cables (included)	1 x VGA cable (VGA to VGA and PS/2), 1.2 m / 4 ft. 1 x USB cable (type A to type B), 1.2 m / 4 ft.
Supported OS	Windows 7/Vista/XP/2000, Linux
Resolution	Up to 100 m (328 ft.) with 1600 x 1200 resolution Up to 150 m (490 ft.) with 1280 x 1024 resolution
Power	9V DC, 1A
LEDs	Power, Link
Dimensions (L x W x H)	130 x 65 x 25 mm (5 x 2.6 x 1 in.)
Weight	Transmitter (local device): 275 g (9.7 oz.) Receiver (remote device): 290 g (10 oz.)
Temperature	Operating: 0° ~ 40° C (32° ~ 104° F) Storage: -20° ~ 60° C (-4° ~ 140° F)
Humidity	Max. 90% (Non-Condensing)
Certifications	CE, FCC

1. Eu preciso utilizar o adaptador de tensão fornecido?

Sim, o adaptador de tensão fornecido tem de ser usado com o Chaveador KVM TK-EX3.

2. O TK-EX3 está corretamente conectado mas meu teclado e meu mouse não funcionam. O que devo fazer?

1. Certifique-se de que o adaptador de tensão está conectado ao TK-EX3.
2. Certifique-se de que seu mouse e seu teclado estão funcionando adequadamente conectando-os diretamente às portas PS/2 de seu computador.
3. Experimente utilizar outro conjunto de mouse e teclado PS/2.

3. Há distorção de imagem quando eu conecto o monitor ao receptor TK-EX3 (dispositivo remoto). O que devo fazer?

1. Você pode ajustar a qualidade do vídeo nos botões Gain (ajuste de resolução) e Equalization (correção de contraste) do receptor TK-EX3 (dispositivo remoto).
2. Se você está usando um cabo com mais de 100 metros, você precisa diminuir a resolução de seu computador para 1280 x 1024. A seguir o comprimento máximo de cabo suportado pelo TK-EX3:

Até 100 metros com resolução 1600 x 1200

Até 150 metros com resolução 1280 x 1024

Se você ainda encontrar dificuldades ou tiver quaisquer perguntas relativas ao **TK-EX3** favor contactar o Departamento de Suporte Técnico da TRENDnet.

Limited Warranty

TRENDnet warrants its products against defects in material and workmanship, under normal use and service, for the following lengths of time from the date of purchase.

TK-EX3 - 2 Year Limited Warranty AC/DC Power Adapter, Cooling Fan and Power Supply carry a 1 year limited warranty

If a product does not operate as warranted during the applicable warranty period, TRENDnet shall reserve the right, at its expense, to repair or replace the defective product or part and deliver an equivalent product or part to the customer. The repair/replacement unit's warranty continues from the original date of purchase. All products that are replaced become the property of TRENDnet. Replacement products may be new or reconditioned. TRENDnet does not issue refunds or credit. Please contact the point-of-purchase for their return policies.

TRENDnet shall not be responsible for any software, firmware, information, or memory data of customer contained in, stored on, or integrated with any products returned to TRENDnet pursuant to any warranty.

There are no user serviceable parts inside the product. Do not remove or attempt to service the product by any unauthorized service center. This warranty is voided if (i) the product has been modified or repaired by any unauthorized service center, (ii) the product was subject to accident, abuse, or improper use (iii) the product was subject to conditions more severe than those specified in the manual.

Warranty service may be obtained by contacting TRENDnet within the applicable warranty period and providing a copy of the dated proof of the purchase. Upon proper submission of required documentation a Return Material Authorization (RMA) number will be issued. An RMA number is required in order to initiate warranty service support for all TRENDnet products. Products that are sent to TRENDnet for RMA service must have the RMA number marked on the outside of return packages and sent to TRENDnet prepaid, insured and packaged appropriately for safe shipment. Customers shipping from outside of the USA and Canada are responsible for return shipping fees. Customers shipping from outside of the USA are responsible for custom charges, including but not limited to, duty, tax, and other fees.

WARRANTIES EXCLUSIVE: IF THE TRENDNET PRODUCT DOES NOT OPERATE AS WARRANTED ABOVE, THE CUSTOMER'S SOLE REMEDY SHALL BE, AT TRENDNET'S OPTION, REPAIR OR REPLACE. THE FOREGOING WARRANTIES AND REMEDIES ARE EXCLUSIVE AND ARE IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED OR IMPLIED, EITHER IN FACT OR BY OPERATION OF LAW, STATUTORY OR OTHERWISE, INCLUDING WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. TRENDNET NEITHER ASSUMES NOR AUTHORIZES ANY OTHER PERSON TO ASSUME FOR IT ANY OTHER LIABILITY IN CONNECTION WITH THE SALE, INSTALLATION MAINTENANCE OR USE OF TRENDNET'S PRODUCTS.

TRENDNET SHALL NOT BE LIABLE UNDER THIS WARRANTY IF ITS TESTING AND EXAMINATION DISCLOSE THAT THE ALLEGED DEFECT IN THE PRODUCT DOES NOT EXIST OR WAS CAUSED BY CUSTOMER'S OR ANY THIRD PERSON'S MISUSE, NEGLIGENCE, IMPROPER INSTALLATION OR TESTING, UNAUTHORIZED ATTEMPTS TO REPAIR OR MODIFY, OR ANY OTHER CAUSE BEYOND THE RANGE OF THE INTENDED USE, OR BY ACCIDENT, FIRE, LIGHTNING, OR OTHER HAZARD.

LIMITATION OF LIABILITY: TO THE FULL EXTENT ALLOWED BY LAW TRENDNET ALSO EXCLUDES FOR ITSELF AND ITS SUPPLIERS ANY LIABILITY, WHETHER BASED IN CONTRACT OR TORT (INCLUDING NEGLIGENCE), FOR INCIDENTAL, CONSEQUENTIAL, INDIRECT, SPECIAL, OR PUNITIVE DAMAGES OF ANY KIND, OR FOR LOSS OF REVENUE OR PROFITS, LOSS OF BUSINESS, LOSS OF INFORMATION OR DATE, OR OTHER FINANCIAL LOSS ARISING OUT OF OR IN CONNECTION WITH THE SALE, INSTALLATION, MAINTENANCE, USE, PERFORMANCE, FAILURE, OR INTERRUPTION OF THE POSSIBILITY OF SUCH DAMAGES, AND LIMITS ITS LIABILITY TO REPAIR, REPLACEMENT, OR REFUND OF THE PURCHASE PRICE PAID, AT TRENDNET'S OPTION. THIS DISCLAIMER OF LIABILITY FOR DAMAGES WILL NOT BE AFFECTED IF ANY REMEDY PROVIDED HEREIN SHALL FAIL OF ITS ESSENTIAL PURPOSE.

Governing Law: This Limited Warranty shall be governed by the laws of the state of California.

Some TRENDnet products include software code written by third party developers. These codes are subject to the GNU General Public License ("GPL") or GNU Lesser General Public License ("LGPL").

Go to <http://www.trendnet.com/gpl> or <http://www.trendnet.com> Download section and look for the desired TRENDnet product to access to the GPL Code or LGPL Code. These codes are distributed WITHOUT WARRANTY and are subject to the copyrights of the developers. TRENDnet does not provide technical support for these codes. Please go to <http://www.gnu.org/licenses/gpl.txt> or <http://www.gnu.org/licenses/lgpl.txt> for specific terms of each license.

PWP05202009v2

Certifications

This equipment has been tested and found to comply with FCC and CE Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference.
- (2) This device must accept any interference received. Including interference that may cause undesired operation.



Waste electrical and electronic products must not be disposed of with household waste. Please recycle where facilities exist. Check with you Local Authority or Retailer for recycling advice.



NOTE: THE MANUFACTURER IS NOT RESPONSIBLE FOR ANY RADIO OR TV INTERFERENCE CAUSED BY UNAUTHORIZED MODIFICATIONS TO THIS EQUIPMENT. SUCH MODIFICATIONS COULD VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT.

ADVERTENCIA

En todos nuestros equipos se mencionan claramente las características del adaptador de alimentación necesario para su funcionamiento. El uso de un adaptador distinto al mencionado puede producir daños físicos y/o daños al equipo conectado. El adaptador de alimentación debe operar con voltaje y frecuencia de la energía eléctrica domiciliar existente en el país o zona de instalación.



Product Warranty Registration

Please take a moment to register your product online.
Go to TRENDnet's website at <http://www.trendnet.com/register>