



8-Port 100Base-FX SC Type Multi-Mode Fiber Module

TEG-S3M8FX

FEATURES

- Compliant with IEEE 802.3u 100Base-FX
- 8 x 100Base-FX Multi-Mode SC Type Fiber Port (TEG-S3M8FX)
- 8 x 100Base-FX Single-Mode SC Type Fiber Port (TEG-S3M8S15)
- Optional Modules for TEG-S3000i (Layer 2 Managed Chassis Switch)
- 5-Year Warranty

8-Port 100Base-FX SC Type Multi-Mode Fiber Module

TEG-S3M8FX

SPECIFICATIONS

Hardware	
Standards	<ul style="list-style-type: none">• IEEE 802.3u 100Base-FX• IEEE 802.3x flow control
Interface	<ul style="list-style-type: none">• 8 x 100FX (Multi Mode or Single Mode) SC-Type Ports
Network Media	<ul style="list-style-type: none">• 50/125 um or 62.5/125um for Multi-Mode Fiber Optic, Up to 2km• 8/125um or 9/125um for Single-Mode Fiber Optic, Up to 15km
Switch Architecture	<ul style="list-style-type: none">• Store/Forward
LED	<ul style="list-style-type: none">• Link, Activity
Connector	<ul style="list-style-type: none">• SC
Protocol	<ul style="list-style-type: none">• CSMA/CD
Wavelength	<ul style="list-style-type: none">• 1310nm
Range	<ul style="list-style-type: none">• Single-Mode: 30km• Multi-Mode: 2km
Dimensions	<ul style="list-style-type: none">• 126 x 46 x 35mm (5.0 x 1.8 x 1.4 in.)
Weight	<ul style="list-style-type: none">• 88g (3.1oz.)
Temperature	<ul style="list-style-type: none">• Operating: 0°~45°C (32°~113°F)• Storage: -10°~70°C (14°~158°F)
Humidity	<ul style="list-style-type: none">• 10%~90% (non-condensing)
Certification	<ul style="list-style-type: none">• CE, FCC



PACKAGE CONTENTS

• TEG-S3M8FX

RELATED PRODUCTS

TEG-S3000i	4-Slot Gigabit Layer 2 Managed Chassis
TEG-S3M8FX	8-Port 100Base-FX SC Type Multi-Mode Fiber Module
TEG-S3M8S15	8-Port 100Base-FX SC Type Single-Mode Fiber Module
TEG-S3M2MG	2 Mini-GBIC Slot
TEG-S3M11CF	Gigabit Copper and Fiber Combo
TEG-S3M2CG	2 Gigabit Copper Port

ORDERING INFORMATION

TRENDnet

3135 Kashiwa Street, Torrance, CA 90505 USA
Tel: 1-310-891-1100
Fax: 1-310-891-1111
Web: www.trendnet.com
Email: sales@trendnet.com

To Order Please Call:

1-888-326-6061