



# Magnetic Dual Antenna Mounting Base RP-SMA Female with RP-SMA Male Extension Cable

TEW-LB101 (1.0R)

- Extends two wireless antennas up to 1m (3.3 ft.)
- Magnetic base allows for easy mounting, positioning, and optimal placement of antennas
- Compatible with 2.4GHz or 5GHz directional and omni-directional RP-SMA detachable antennas

TRENDnet's Dual Antenna Magnetic Mounting Base RP-SMA Female with RP-SMA Male Extension Cable, model TEW-LB101, extends two wireless antennas up to 1m (3.3 ft.) and can be used with wireless routers, access points, and wireless network adapters that use detachable RP-SMA antennas. The magnetic mounting base provides convenient placement and positioning of antennas to attain optimal signal range.



# **FEATURES**



#### Interface

Dual RP-SMA plug (female) mounting base to RP-SMA (male) cable



# Installation Flexibility

Magnetic base along with 1m (3.3 ft.) cable allows for easy mounting, positioning, and placement of antennas for optimal signal range



# Compatibility

 Compatible with 2.4GHz or 5GHz directional and omni-directional RP-SMA detachable antennas

# **NETWORKING SOLUTION**



# **SPECIFICATIONS**

## Connector

• 2 x RP-SMA male connectors (magnetic base) to RP-SMA female connectors (cable)

#### **Cable Length**

• 1m (3.3 ft)

#### Cable Loss

• Max 3dB

## **Dimension**

- Base: 91 x 19 x 78mm (3.58 x 0.74 x 3.07 in.)
- Cable: 1m (3.3ft.)

#### Weight

- Base + Cable: 114g (4 oz.)
- Base only: 71.1g (2.5 oz.)

## **Operating Temperature**

• 0° - 55° C (32° - 131° F)

#### **Operating Humidity**

• Max. 95% non-condensing

## Antenna Base

Magnetic antenna base

#### **Package Contents**

• TEW-LB101



All references to speed are for comparison purposes only. Product specifications, size, and shape are subject to change without notice, and actual product appearance may differ from that depicted herein.