



## USB to PS/2 Converter

### TU-PS2 (v2.0R)

This USB to PS/2 Converter allows you to connect a PS/2 keyboard and mouse to a USB port on your Desktop or Laptop PC.

## PRODUCT OVERVIEW

- Connect a PS/2 keyboard and mouse to a USB port on your computer
- Easy installation with Universal Plug and Play (UPnP)
- Supports multiple operating systems

## FEATURES

- Compliant with USB 1.1 and USB 1.0 specifications
- Converts two PS/2 devices simultaneously (keyboard and mouse) to the USB interface
- Converts the PS/2 port on the KVM switch to USB KVM device (PC, Mac or SUN Platforms)
- Supports standard PS/2 mouse and Microsoft IntelliMouse
- Supports data transfer rate up to 12 Mbps
- Supports BUS-Power, no external power adapter required
- Simple Plug & Play installation
- 2-year limited warranty



## SPECIFICATIONS

### HARDWARE

<b>Interface</b>	<ul style="list-style-type: none"><li>• USB 1.1/1.0 interface type A</li><li>• PS/2</li></ul>
<b>Standards</b>	<ul style="list-style-type: none"><li>• PS/2 Keyboard &amp; Mouse</li></ul>
<b>OS Compliant</b>	<ul style="list-style-type: none"><li>• Windows 8, Windows 7(32/64-bit), Vista (32/64-bit), XP(32/64-bit), 2000, ME, 98SE</li><li>• Mac OS X 10.1 ~ 10.6</li></ul>
<b>Cable Length</b>	<ul style="list-style-type: none"><li>• 33.8 cm (13 in.)</li></ul>
<b>Cable Gauge</b>	<ul style="list-style-type: none"><li>• 28/24 AWG</li></ul>
<b>Data Rate</b>	<ul style="list-style-type: none"><li>• 1.5 Mbps</li></ul>
<b>Power Consumption</b>	<ul style="list-style-type: none"><li>• 500 mA (max)</li></ul>
<b>Weight</b>	<ul style="list-style-type: none"><li>• 45 g (1.59 oz.)</li></ul>
<b>Temperature</b>	<ul style="list-style-type: none"><li>• Operating: 5°C ~ 40°C (41°F ~ 104°F)</li><li>• Storage: -20°C ~ 60°C (-4°F ~ 140°F)</li></ul>
<b>Humidity</b>	<ul style="list-style-type: none"><li>• Max 85% (non-condensing)</li></ul>
<b>Certifications</b>	<ul style="list-style-type: none"><li>• CE, FCC</li></ul>

## NETWORKING SOLUTIONS



## PACKAGE CONTENTS

TU-PS2

Quick Installation Guide

## RELATED PRODUCTS

<b>TU-S9</b>	USB to Serial Converter
<b>TU-P1284</b>	USB to Parallel 1284 Converter
<b>TU2-ET100</b>	USB to 10/100 Mbps Adapter

## CONTACT INFORMATION

**TRENDnet**

20675 Manhattan Place, Torrance, CA 90501 USA

Tel: 1-310-961-5500

Fax: 1-310-961-5511

Web: [www.trendnet.com](http://www.trendnet.com)

Email: [sales@trendnet.com](mailto:sales@trendnet.com)

**1-888-326-6061**

