



## 15 ft. DVI-I, USB, and Audio KVM Cable Kit

TK-CD15 (v1.0R)

- Compatible with the TK-232DV KVM Switch
- DVI-I cable interface
- USB cable for mouse and keyboard connections
- 3.5mm cables for microphone and speaker connections

TRENDnet's 15 ft. DVI-I, USB, and Audio KVM Cable Kit, model TK-CD15, is designed to connect a DVI computer to the TRENDnet TK-232DV KVM switch. The cable kit consists of a USB mouse/keyboard, DVI-I, and 3.5mm audio connections for a single computer.



**DVI-I**

Designed to connect a DVI-I computer to the TK-232DV KVM Switch



**USB**

A single USB cable for USB mouse/keyboard connection



**Audio Support**

Features 3.5mm speaker and microphone connections for full audio support

## Specifications

<b>KVM interface</b>	<ul style="list-style-type: none"> <li>• Keyboard/Mouse: USB Type B</li> <li>• Monitor: DVI-I</li> <li>• Speaker jack: 3.5mm</li> <li>• Microphone jack: 3.5mm</li> </ul>
<b>PC interface</b>	<ul style="list-style-type: none"> <li>• Keyboard/Mouse: USB Type A</li> <li>• Monitor: DVI-I</li> <li>• Speaker jack: 3.5mm</li> <li>• Microphone jack: 3.5mm</li> </ul>
<b>Operating Temperature</b>	• 0° – 40° C (32° – 104° F)
<b>Operating Humidity</b>	• Max. 90 % non-condensing
<b>Length</b>	• 4.57m (15 ft.)
<b>Weight</b>	• 726g (25.6 oz.)
<b>Warranty</b>	• 2 year

PACKAGE CONTENTS
• TK-CD15

All references to speed are for comparison purposes only. Product specifications, size, and shape are subject to change without notice, and actual product appearance may differ from that depicted herein.